

Pointwise completeness and pointwise degeneracy of fractional descriptor continuous-time linear systems with regular pencils

T. KACZOREK*

Faculty of Electrical Engineering, Białystok University of Technology, 45D Wiejska St., 15-351 Białystok, Poland

Abstract. Pointwise completeness and pointwise degeneracy of the fractional descriptor continuous-time linear systems with regular pencils are addressed. Conditions for the pointwise completeness and pointwise degeneracy of the systems are established and illustrated by an example.

Key words: pointwise completeness, pointwise degeneracy, descriptor, fractional, continuous-time, linear, system.

1. Introduction

Descriptor (singular) linear systems have been considered in many papers and books [1–14]. The eigenvalues and invariants assignment by feedbacks have been investigated in [9, 10] and the minimum energy control of descriptor linear systems in [11]. The stability of positive descriptor systems has been investigated in [14]. The positive linear systems with different fractional orders have been addressed in [15]. Descriptor standard positive linear systems by the use of Drazin inverse have been addressed in [1, 2, 8, 10, 16]. The shuffle algorithm has been applied to checking the positivity of descriptor linear systems in [7]. The reduction and decomposition of descriptor fractional discrete-time linear systems have been considered in [12]. A new class of descriptor fractional linear discrete-time system has been introduced in [15]. The pointwise completeness and pointwise degeneracy for standard linear systems have been investigated in [17–27] and for fractional linear systems in [17, 20, 22]. The Drazin inverse of matrices has been applied to find the solutions of the state equations of the fractional descriptor continuous-time linear systems with regular pencils in [8].

In this paper the pointwise completeness and pointwise degeneracy of the fractional descriptor continuous-time linear systems with regular pencil is addressed.

The paper is organized as follows. In Sec. 2 some definitions, lemmas and theorems concerning the fractional descriptor continuous-time linear systems are recalled. The main result of the paper is presented in Sec. 3, where the conditions for the pointwise completeness and pointwise degeneracy of the fractional descriptor continuous-time linear systems with regular pencils are established and illustrated by an example. Concluding remarks are given in Sec. 4.

The following notation is used: \mathbb{R} – the set of real numbers, $\mathbb{R}^{n \times m}$ – the set of $n \times m$ real matrices and $\mathbb{R}^n = \mathbb{R}^{n \times 1}$, Z_+ – the set of $n \times n$ nonnegative matrices, I_n – the $n \times n$ identity matrix, $\ker A$ (im A) – the kernel (image) of the matrix A .

2. Preliminaries

Consider the autonomous fractional descriptor continuous-time linear system

$${}_0D_t^\alpha x(t) = Ax(t), \quad 0 < \alpha < 1, \quad (1)$$

where α is fractional order, $x(t) \in \mathbb{R}^n$ is the state vector, $E, A \in \mathbb{R}^{n \times n}$ and

$${}_0D_t^\alpha x(t) = \frac{1}{\Gamma(1-\alpha)} \int_0^t \frac{1}{(t-\tau)^\alpha} \frac{dx(\tau)}{d\tau} d\tau \quad (2)$$

is the Caputo definition of $\alpha \in \mathbb{R}$ order derivative of $x(t)$ and

$$\Gamma(\alpha) = \int_0^\infty e^{-t} t^{\alpha-1} dt \quad (3)$$

is the Euler gamma function.

It is assumed that $\det E = 0$ but the pencil (E, A) of (1) is regular, i.e.

$$\det[Es - A] \neq 0 \text{ for some } s \in \mathbb{C} \quad (4)$$

(the field of complex numbers).

Assuming that for some chosen $c \in \mathbb{C}$, $\det[Ec - A] \neq 0$ and premultiplying (1) by $[Ec - A]^{-1}$ we obtain

$$\overline{E} {}_0D_t^\alpha x(t) = \overline{A}x(t), \quad (5a)$$

where

$$\overline{E} = [Ec - A]^{-1}E, \quad \overline{A} = [Ec - A]^{-1}A. \quad (5b)$$

Note that the Eqs. (1) and (5a) have the same solution $x(t)$.

Definition 1. [3, 10]. The smallest nonnegative integer q is called the index of the matrix $\overline{E} \in \mathbb{R}^{n \times n}$ if

$$\text{rank } \overline{E}^q = \text{rank } \overline{E}^{q+1}. \quad (6)$$

Definition 2. [3, 8, 10]. A matrix \overline{E}^D is called the Drazin inverse of $\overline{E} \in \mathbb{R}^{n \times n}$ if it satisfies the conditions

$$\overline{E}\overline{E}^D = \overline{E}^D\overline{E}, \quad (7a)$$

*e-mail: kaczkorek@isep.pw.edu.pl

$$\overline{E}^D \overline{E} \overline{E}^D = \overline{E}^D, \quad (7b)$$

$$\overline{E}^D \overline{E}^{q+1} = \overline{E}^q, \quad (7c)$$

where q is the index of \overline{E} defined by (6).

The Drazin inverse \overline{E}^D of a square matrix \overline{E} always exists and is unique [3, 10]. If $\det \overline{E} \neq 0$ then $\overline{E}^D = \overline{E}^{-1}$. Some methods for computation of the Drazin inverse are given in [10].

Lemma 1. [3, 8, 10]. The matrices \overline{E} and \overline{A} defined by (5b) satisfy the following equalities

$$\begin{aligned} 1. \quad & \overline{A}\overline{E} = \overline{E}\overline{A} \quad \text{and} \quad \overline{A}^D \overline{E} = \overline{E}\overline{A}^D, \\ & \overline{E}^D \overline{A} = \overline{A}\overline{E}^D, \quad \overline{A}^D \overline{E}^D = \overline{E}^D \overline{A}^D, \end{aligned} \quad (8a)$$

$$2. \quad \ker \overline{A} \cap \ker \overline{E} = \{0\}, \quad (8b)$$

$$\begin{aligned} 3. \quad & \overline{E} = T \begin{bmatrix} J & 0 \\ 0 & N \end{bmatrix} T^{-1}, \\ & \overline{E}^D = T \begin{bmatrix} J^{-1} & 0 \\ 0 & 0 \end{bmatrix} T^{-1}, \end{aligned} \quad (8c)$$

$\det T \neq 0$, $J \in \mathbb{R}^{n_1 \times n_1}$, is nonsingular, $N \in \mathbb{R}^{n_2 \times n_2}$ is nilpotent, $n_1 + n_2 = n$,

$$\begin{aligned} 4. \quad & (I_n - \overline{E}\overline{E}^D)\overline{A}\overline{A}^D = I_n - \overline{E}\overline{E}^D \\ & \text{and} \quad (I_n - \overline{E}\overline{E}^D)(\overline{E}\overline{A}^D)^q = 0. \end{aligned} \quad (8d)$$

Theorem 1. [8] The solution to the Eq. (1) is given by

$$x(t) = \Phi_0(t) \overline{E}\overline{E}^D w, \quad (9a)$$

where

$$\Phi_0(t) = \sum_{k=0}^{\infty} \frac{(\overline{E}^D \overline{A})^k t^{k\alpha}}{\Gamma(k\alpha + 1)} \quad (9b)$$

and the vector $w \in \mathbb{R}^n$ is arbitrary.

From (9a) we have $x(0) = x_0 = \overline{E}\overline{E}^D v$ and $x_0 \in \text{im}(\overline{E}\overline{E}^D)$ where im denotes the image of $\overline{E}\overline{E}^D$.

Lemma 2. The matrix $\Phi_0(t)$ defined by (9b) is nonsingular for any matrix $A \in \mathbb{R}^{n \times n}$ and time $t \geq 0$.

Proof is given in [8].

Theorem 2. Let

$$P = \overline{E}\overline{E}^D \quad \text{and} \quad Q = \overline{E}^D \overline{A}. \quad (10)$$

Then:

$$1) P^k = P \text{ for } k = 2, 3, \dots, \quad (11a)$$

$$2) PQ = QP = Q, \quad (11b)$$

$$3) P\Phi_0(t) = \Phi_0(t). \quad (11c)$$

Proof is given in [8].

3. Pointwise completeness and pointwise degeneracy

Definition 3. The fractional descriptor system (1) is called pointwise complete for $t = t_f$ if for every final state $x_f \in \mathbb{R}^n$ there exists a vector of initial conditions $x_0 \in \text{Im}(\overline{E}\overline{E}^D)$ such that $x(t_f) = x_f$.

Theorem 3. The fractional descriptor system (1) is pointwise complete for any $t = t_f$ and every final state $x_f \in \mathbb{R}^n$ belonging to the set

$$x_f = \text{im}[\Phi_0(t_f)x_0]. \quad (12)$$

Proof. Substituting in (9a) $t = t_f$ we obtain

$$x_f = x(t_f) = \Phi_0(t_f)x_0 \quad (13)$$

and

$$x_0 = [\Phi_0(t_f)]^{-1}x_f \quad (14)$$

since by Lemma 2 the matrix $\Phi_0(t)$ is nonsingular for any matrix $\overline{E}^D \overline{A}$ and time $t \geq 0$.

Definition 4. The fractional descriptor system (1) is called pointwise degenerated in the direction v for $t = t_f$ if there exists a nonzero vector $v \in \mathbb{R}^n$ such that for all initial conditions $x_0 \in \text{Im}(\overline{E}\overline{E}^D)$ the solution of (1) satisfy the condition

$$v^T x_f = 0 \quad (15)$$

where T denotes the transpose.

Theorem 4. The fractional descriptor system (1) is pointwise degenerated in the direction v defined by

$$v^T \overline{E} = 0 \quad (16)$$

for any $t_f \geq 0$ and all initial conditions $x_0 \in \text{Im}(\overline{E}\overline{E}^D)$.

Proof. Postmultiplying (16) by $\overline{E}^D w$ and using $x_0 = \overline{E}\overline{E}^D w$ and (15) we obtain

$$v^T \overline{E}\overline{E}^D w = v^T x_0 = 0. \quad (17)$$

Taking into account (9b), (13) and (16) we obtain

$$\begin{aligned} v^T x_f &= v^T \Phi_0(t_f)x_0 = \sum_{k=0}^{\infty} \frac{v^T (\overline{E}^D \overline{A})^k t_f^{k\alpha}}{\Gamma(k\alpha + 1)} x_0 \\ &= v^T x_0 + \sum_{k=1}^{\infty} \frac{v^T \overline{E}\overline{E}^D (\overline{E}^D \overline{A})^k t_f^{k\alpha}}{\Gamma(k\alpha + 1)} x_0 = 0 \end{aligned} \quad (18)$$

since (7b) and (16) holds.

Example 1. Consider the system (1) with the matrices

$$E = \begin{bmatrix} 1 & 0 \\ 0 & 0 \end{bmatrix}, \quad A = \begin{bmatrix} -1 & 0 \\ 0 & -2 \end{bmatrix}, \quad 0 < \alpha < 1. \quad (19)$$

The pencil of (19) is regular since

$$\det[Es - A] = \begin{vmatrix} s+1 & 0 \\ 0 & 2 \end{vmatrix} = 2(s+1) \neq 0. \quad (20)$$

and the assumption (4) is met.

Choosing $c = 1$ we obtain

$$\begin{aligned}\overline{E} &= [Ec - A]^{-1}E \\ &= \begin{bmatrix} 2 & 0 \\ 0 & 2 \end{bmatrix}^{-1} \begin{bmatrix} 1 & 0 \\ 0 & 0 \end{bmatrix} = \begin{bmatrix} 0.5 & 0 \\ 0 & 0 \end{bmatrix},\end{aligned}\quad (21)$$

$$\begin{aligned}\overline{A} &= [Ec - A]^{-1}A \\ &= \begin{bmatrix} 2 & 0 \\ 0 & 2 \end{bmatrix}^{-1} \begin{bmatrix} -1 & 0 \\ 0 & -2 \end{bmatrix} = \begin{bmatrix} -0.5 & 0 \\ 0 & -1 \end{bmatrix}\end{aligned}$$

and

$$\overline{E}^D = \begin{bmatrix} 2 & 0 \\ 0 & 0 \end{bmatrix} \quad \text{and} \quad \overline{A}^D = \begin{bmatrix} -2 & 0 \\ 0 & -1 \end{bmatrix}. \quad (22)$$

In this case the admissible initial conditions are

$$\begin{aligned}x_0 &= \text{im}(\overline{E}\overline{E}^D) = \text{im} \begin{bmatrix} 1 & 0 \\ 0 & 0 \end{bmatrix} = \begin{bmatrix} x_{10} \\ 0 \end{bmatrix} \\ \text{and } x_{10} &\text{ is arbitrary.}\end{aligned}\quad (23)$$

Using (9b) and (22) we obtain the nonsingular matrix

$$\begin{aligned}\Phi_0(t) &= \sum_{k=0}^{\infty} \frac{(\overline{E}^D \overline{A})^k t^{k\alpha}}{\Gamma(k\alpha + 1)} \\ &= \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} + \sum_{k=1}^{\infty} \frac{t^{k\alpha}}{\Gamma(k\alpha + 1)} \begin{bmatrix} -1 & 0 \\ 0 & 0 \end{bmatrix}^k \\ &= \begin{bmatrix} 1 + \varphi(t) & 0 \\ 0 & 1 \end{bmatrix},\end{aligned}\quad (24a)$$

where

$$\varphi(t) = \sum_{k=1}^{\infty} \frac{(-1)^k t^{k\alpha}}{\Gamma(k\alpha + 1)}. \quad (24b)$$

By Theorem 3 the fractional descriptor system (1) with (19) is pointwise complete for $t = t_f$ and every $x_f \in \mathbb{R}^2$ satisfying the condition (12). In this case from (14) and (24a), (24b) we have

$$\begin{aligned}x_0 &= [\Phi_0(t_f)]^{-1}x_f = \begin{bmatrix} [1 + \varphi(t_f)]^{-1}x_{1f} \\ 0 \end{bmatrix} \\ &\in \text{im}(\overline{E}\overline{E}^D) = \begin{bmatrix} x_{10} \\ 0 \end{bmatrix}\end{aligned}\quad (25)$$

if and only if $x_f \in \text{Im}(\overline{E}\overline{E}^D) = \begin{bmatrix} x_{1f} \\ 0 \end{bmatrix}$, where x_{1f} is arbitrary.

By Theorem 4 the system (1) with (19) is pointwise degenerated in the direction $v^T = [0 \quad v_2]$ for any v_2 since

$$v^T \overline{E} = [0 \quad v_2] \begin{bmatrix} 0.5 & 0 \\ 0 & 0 \end{bmatrix} = [0 \quad 0]. \quad (26)$$

4. Concluding remarks

The pointwise completeness and the pointwise degeneracy of the fractional descriptor continuous-time linear systems with regular pencil have been addressed. The conditions for the pointwise completeness and the pointwise degeneracy of the systems have been established (Theorem 3 and 4). The considerations have been illustrated by an numerical example of fractional descriptor system with regular pencil. The considerations can be extended to the positive fractional descriptor linear systems.

Acknowledgements. This work was supported by the National Science Centre in Poland under the work No NN514 6389 40.

REFERENCES

- [1] R. Bru, C. Coll, S. Romero-Vivo, and E. Sanchez, "Some problems about structural properties of positive descriptor systems", *Lecture Notes in Control and Inform. Sci.* 294, 233–240 (2003).
- [2] R. Bru, C. Coll, and E. Sanchez, "Structural properties of positive linear time-invariant difference-algebraic equations", *Linear Algebra Appl.* 349, 1–10 (2002).
- [3] S.L. Campbell, C.D. Meyer, and N.J. Rose, "Applications of the Drazin inverse to linear systems of differential equations with singular constant coefficients", *SIAMJ Appl. Math.* 31, 411–425 (1976).
- [4] L. Dai, *Singular Control Systems*, Springer-Verlag, Berlin, 1989.
- [5] Guang-Ren Duan, *Analysis and Design of Descriptor Linear Systems*, Springer, New York, 2010.
- [6] T. Kaczorek, "Application of Drazin inverse to analysis of descriptor fractional discrete-time linear systems with regular pencils", *Int. J. Appl. Math. Comput. Sci.* 23, 29–33 (2013).
- [7] T. Kaczorek, "Checking of the positivity of descriptor linear systems by the use of the shuffle algorithm", *Archives of Control Sciences* 21, 287–298 (2011).
- [8] T. Kaczorek, "Drazin inverse matrix method for fractional descriptor continuous-time linear systems", *Bull. Pol. Ac.: Tech.* 62, 409–412 (2014).
- [9] T. Kaczorek, "Infinite eigenvalue assignment by output-feedbacks for singular systems", *Int. J. Appl. Math. Comput. Sci.* 14, 19–23 (2004).
- [10] T. Kaczorek, *Linear Control Systems*, vol. 1, Research Studies Press J. Wiley, New York, 1992.
- [11] T. Kaczorek, "Minimum energy control of positive fractional descriptor continuous-time linear systems", *IET Control Theory and Applications*, doi:10.1049/oet-cta.2013.0362, 1–7 (2013).
- [12] T. Kaczorek, "Reduction and decomposition of singular fractional discrete-time linear systems", *Acta Mechanica et Automatica* 5, 62–66 (2011).
- [13] T. Kaczorek, "Singular fractional discrete-time linear systems", *Control and Cybernetics* 40, 753–761 (2011).
- [14] E. Virnik, "Stability analysis of positive descriptor systems", *Linear Algebra and Its Applications* 429, 2640–2659 (2008).
- [15] T. Kaczorek, *Selected Problems of Fractional Systems Theory*, Springer-Verlag, Berlin, 2011.
- [16] T. Kaczorek, *Positive 1D and 2D Systems*, Springer-Verlag, London, 2002.

- [17] M. Buśłowicz, "Pointwise completeness and pointwise degeneracy of linear discrete-time systems of fractional order", *Automatics. Notebooks of the Silesian University of Technology* 151, 19–24 (2008), (in Polish).
- [18] M. Buśłowicz, R. Kociszewski, and W. Trzasko, "Pointwise completeness and pointwise degeneracy of positive discrete-time systems with delays", *Automatics. Notebooks of the Silesian University of Technology* 145, 51–56 (2006), (in Polish).
- [19] A.K. Choudhury, "Necessary and sufficient conditions of pointwise completeness of linear time-invariant delay-differential systems", *Int. J. Control* 16, 1083–1100 (1972).
- [20] T. Kaczorek and M. Buśłowicz, "Pointwise completeness and pointwise degeneracy of linear continuous-time fractional order systems", *J. Automation, Mobile Robotics & Intelligent Systems* 3, 8–11 (2009).
- [21] T. Kaczorek, "Pointwise completeness and pointwise degeneracy of 2D standard and positive Fornasini-Marchesini models", *COMPEL* 30, 656–670 (2011).
- [22] T. Kaczorek, "Pointwise completeness and pointwise degeneracy of standard and positive fractional linear systems with state-feedbacks", *Archives of Control Sciences* 19, 295–306 (2009).
- [23] T. Kaczorek, "Pointwise completeness and pointwise degeneracy of standard and positive linear systems with state-feedbacks", *JAMRIS* 4, 3–7 (2010).
- [24] A. Olbrot, "On degeneracy and related problems for linear constant time-lag systems", *Ricerche di Automatica* 3, 203–220 (1972).
- [25] V.M. Popov, "Pointwise degeneracy of linear time-invariant delay-differential equations", *J. Diff. Equation* 11, 541–561 (1972).
- [26] W. Trzasko, M. Buśłowicz, and T. Kaczorek, "Pointwise completeness of discrete-time cone-systems with delays", *Proc. EUROCON* 1, 606–611 (2007).
- [27] L. Weiss, "Controllability for various linear and nonlinear systems models", *Lecture Notes in Mathematics* 144, *Seminar on Differential Equations and Dynamic System II*, 250–262 (1970).